

AH-00212

Fire Alarm Control Panel



1 ~ 10 Zone



1 Zone

LED Description

- FIRE : Indicates fire status
- Power : Indicates unit is in normal status
- Short C. : Indicates short-circuit
- Discon. : Indicates disconnection
- S.T. : Controls H1 & H2 for activation, light on means inactive
- Bell : Activates unit's sounder and external bell, light on means inactive
- Reset : Turns system back to initial status

Specification

26V DC 100~400mA *With auto adjustment function 26V DC 100~400mA *With auto adjustment function

Model	AH-00212 (1~10 Zone)	AH-00212 (1 Zone)
Power	220V AC/50Hz *Others also available	
Battery Capacity	24V DC 1.2Ah	24V DC 0.8Ah
Charging Voltage, Current	26V DC 100~400mA *With auto adjustment function	
Exterior Resistance	Round-trip under 50Ω	
# of heat detector connected	No limit *Except electronic-type	
# of smoke detector connected	30/zone *Horing Lih manufactured	
Max. Output Current	1A	500mA
Digital Switch	500000 Cycles Min. reliability	
End of Line Resistor	10kΩ *One per zone	
Material	1.2mm steel plate	
Color	Ivory white *Others also available	
Dimensions	350mm (H) x 285mm (W) x 105mm (D)	280mm (H) x 160mm (W) x 70mm (D)



AH-02124 Annunciator

Approvals:

Distributor in Vietnam:

VIET BAO FIREFIGHTING AND PREVENTING EQUIPMENT COMPANY LIMITED.



140 Nguyen Van Thu St (Ground floor), DaKao ward, Dist.1, HCMC.

Tel: 84.28.39101156 – 39101157. Fax: 84.28.39101158

Email: vietbao@vietbaopccc.com.vn Website: <http://vietbaopccc.com.vn>